


## **SN-358 SKYPE** Feature List

<b>Feature</b>		<b>SN-358 SKYPE</b>
Photo		
1	Frequency	268MHz ~ 394MHz (F9)
2	Long Range Cordless	8 - 15Km
3	Multi-channel with auto-scan	○
4	Multi-handset system (up to 99)	○
5	Single Color LCD(Orange)	○
6	Walkie-talkie between H/S	○
7	Vibration mode	○
8	Selectable Ring & Page Tone on H/S & B/S	H/S : 15 B/S : 10
9	H/S with speakerphone function	○
10	H/S with scrolling keys	○
11	Two-way paging & hand-free intercom	○
12	H/S Custom Name Edit	○
13	30 CID memory with Time/Date (FSK & DTMF type)	○
14	CID with call waiting (CIDCW)	○
15	Last 10 calls redial on H/S	○
16	50 Phonebook with name/number on each H/S	○
17	Tone/Pulse dialing mode selectable	○
18	Multi-language display	English / Russian / Arabic / Spanish / Turkish
19	Music on hold	×
20	B/S speakerphone with dial keypad	○
21	20 memory dial on B/S	○
22	B/S unit with last number redial	○
23	LCD and H/S keypad with backlit	○
24	Auto detection of FSK and DTMF CID signal	○
25	Change channel during Conversation	○
26	65,536 sets security codes (two-way)	○

27	Flash time programmable	<input type="radio"/>
28	Ring volume adjustable for both H/S and B/S	<input type="radio"/>
29	Voice volume adjustable for both H/S and B/S	<input type="radio"/>
30	H/S with power saving function	<input type="radio"/>
31	Low battery alert and display	<input type="radio"/>
32	Built- in voice security circuit (Scrambler)	<input type="radio"/>
33	Auto answer and auto hang up	<input type="radio"/>
34	Transferring a call between H/S and B/S	<input type="radio"/>
35	Out-of-range alert	<input type="radio"/>
36	Battery charge indicator	<input type="radio"/>
37	Fast charge	<input type="radio"/>
38	Adjustable Keypad volume on H/S	<input type="radio"/>
39	Auto power control designed	<input type="radio"/>
40	Skype functions:	<input type="radio"/>
41	* PC based Skype	<input type="radio"/>
42	* Free call from Skype to Skype	<input type="radio"/>
43	* Dialling via SkypeOut	<input type="radio"/>
44	* Receiving call from PSTN	<input type="radio"/>
45	* Distinctive ringing between Skype and PSTN	<input type="radio"/>
46	* Skype contacts available on handset	<input type="radio"/>
47	* Making Skype call and PSTN call simultaneously	<input type="radio"/>
48	* Call Log : Missed / Received / Dialed	<input type="radio"/>
51	System Package :	
52	* Handset x 1	<input type="radio"/>
53	* Base x 1	<input type="radio"/>
54	* Battery(1050mAh/3.7V Li-Ion) x 1	<input type="radio"/>
55	* Line cord(RJ-11) x 1	<input type="radio"/>
56	* Power Adaptor x 1	<input type="radio"/>
57	* User Manual x 1 (CD)	<input type="radio"/>
58	* USB cable x 1	<input type="radio"/>
59	* Base antenna x 1	<input type="radio"/>
60	* Installation CD x 1	<input type="radio"/>
61	Handset Package :	
62	* Handset x 1	<input type="radio"/>
63	* Battery(1050mAh/3.7V Li-Ion) x 1	<input type="radio"/>
64	* Travel charger x 1	<input type="radio"/>
65	* Quick Guide x 1	<input type="radio"/>

	<b>Base station</b>	<b>Handset</b>
<b>Transmitter</b>		
Frequency	394 MHz	268 MHz
Output power	1 W	450 m W
Spurious emission	55 dBc	55 dBc
Current consumption		
Stand-by	100 mA	10 mA
Talk	600 mA	420 mA
<b>Receiver</b>		
Frequency	268 MHz	394 MHz
Sensitivity at 12 dB SINAD (CCITT)	-122dBm	-121dBm
Adjacent channel rejection	50 dBc	50 dBc
Spurious response	55 dBc	55 dBc
Power source	AC 110V/220V, 50/60 Hz DC 12V/800mA	3.7V/1050 mAh Li-Ion Battery